

Dell™ with Oracle® 11g Database Standard Edition Running Enterprise Linux



Oracle 11g Database Standard Edition and RAC Running on Enterprise Linux 5.5



Minimum Hardware/Software Requirements (Updated 07/29/11– for details, see below)

	Validated Component(s)	Minimum Single Node DB Config	Minimum Oracle RAC Config
Oracle Software & Licenses	Oracle 11g R2 11.2.0.2.0 Standard Edition	Single Node	RAC (max 2 nodes)
Oracle Patch(es)	Oracle 11g R2 11.2.0.2		
Operating System	Red Hat Enterprise Linux 5.5 with kernel 2.6.18-194.3.1 Oracle Enterprise Linux 5.5 with kernel 2.6.18-194.32.1.0.1		
Recommended Support Contract	Dell ProSupport and Oracle supported		
Supported PowerEdge Servers	PowerEdge 1950 III, 2950 III, 2900 III, R610, R710, R610 II, R715, T610, T710, T610 II, T710 II	1 Only	2
Memory	All valid PowerEdge memory configurations	Minimum supported	Minimum supported
Dell PowerVault Storage Array	Dell PowerVault MD3000/MD32XX (SAS) and MD3000i/MD32XXi (iSCSI) w/ MD1000/MD 12XX Expansion	N/A (For Internal Storage) 1 (For External Storage)	1
Dell EqualLogic iSCSI Storage Array	PS4000X/XV, 6000X/XV/S/E ² , 6010X/XV/S/E ² , 6510X	N/A (For Internal Storage) 1 (For External Storage)	1
Dell Compellent	SC-30 ⁵ , SC-40 ⁵	N/A (For Internal Storage) 1 (For External Storage)	1
Fibre Channel Switch		N/A	N/A (For Direct Attached) 2 (8 port switches for 2-4 nodes, and 16 port switches for 5 or more nodes) ¹
HBAs	Qlogic - QLE2460, QLE2462, QLE2562 Emulex - LPe1150e LPe11002, LPe12000, LPe12002	N/A (For Internal Storage) 2 (For External Storage)	2 ports (Per Node) ²
Ethernet Interfaces	Intel or Broadcom 1GbE NICs Intel 10GbE Server Adapters (AT, XF SR, AF DA) Broadcom 10GbE 57710/57711	1	3 (Per Node) ³
Ethernet Switches for iSCSI Storage Area Network	Dell PowerConnect 62xx GbE, PowerConnect 54xx GbE, PowerConnect 8024, 8024F 10GbE	2	2
Ethernet Switches (For Private Interconnect)	1/10GbE Switches	N/A	2
Raid Controllers (Used for internal storage only)	PERC 5/i, PERC 6i, SAS 6/iR, H200, H700	1	1 (Per Node)
Internal Drive	All valid PowerEdge internal storage configurations	73 GB	73 GB/node

For more information, visit Dell.com/Oracle

Oracle 11g Database Standard Edition and RAC Running on Enterprise Linux 5.5



Dell PowerEdge Servers				
Dell PowerEdge™ Servers	Model	BIOS ⁴	ESM - BMC Firmware ⁴	Notes
	PE 1950 III, PE 2900 III, PE 2950 III	2.7.0	2.37	
	PE R610, PE R710, PE R610 II, PE R710 II	3.0.0	1.70,A02 (iDRAC6)	
	PE T610, PE T610 II	3.0.0	1.70,A02 (iDRAC6)	
	PE T710, PE T710 II	3.0.0	1.70,A02 (iDRAC6)	
	PE R715	1.5.2	1.70,A02 (iDRAC6)	

Internal Disks RAID	
H700	Firmware version = 3.0-0032; Driver version = 00.00.04.31.2-1, A12
H200 (mpt2sas)	Firmware version = 07.01.34.00; Driver version = 07.00.01.00-1, A03
PERC 5/i	Firmware version = 5.2.2-0072; Driver version = 00.00.04.31.2-1, A12
PERC 6/i	Firmware version = 6.2.0-0013; Driver version = 00.00.04.31.2-1, A12
SAS 6/iR (mptsas)	Firmware version = 00.25.57.00; Driver version = 4.00.38.02-3, A03

Network Interconnect	
Intel Proset GbE Family of Adapters	Driver version (e1000) = 7.3.21-k4-NAPI
Intel PROSet PT/PF Single/Dual Port Server Adapters	Driver version (e1000e) = 1.1.19-NAPI
Intel Dual Port (ET)/Quad Port (VT/ET) GbE Server Adapters	Driver version (igb) = 2.3.4
Intel 10 GbE (AT/XF SR/AF DA) Server Adapters	Driver version (ixgbe) = 3.2.9-NAPI
Broadcom NetXtreme II GbE Family of Adapters	Driver version (bnx2) = 2.0.23b
Broadcom NetXtreme GbE Family of Adapters	Driver version (tg3) = 3.115j
Broadcom NetXtreme II 10 GbE (57710/57711) Family of Adapters	Driver version (bnx2x) = 1.62.15
Broadcom iSCSI Offload Engine (iSOE)	Driver version (bnx2i) = 2.6.2.4c
NIC Teaming	
Native teaming driver	Driver version (bonding) = 3.4.0

For more information, visit Dell.com/Oracle

Oracle 11g Database Standard Edition and RAC Running on Enterprise Linux 5.5



Network Interconnect

Intel Proset GbE Family of Adapters	Driver version (e1000) = 7.3.21-k4-NAPI
Intel PROSet PT/PF Single/Dual Port Server Adapters	Driver version (e1000e) = 1.1.19-NAPI
Intel Dual Port (ET)/Quad Port (VT/ET) GbE Server Adapters	Driver version (igb) = 2.3.4
Intel 10 GbE (AT/XF SR/AF DA) Server Adapters	Driver version (ixgbe) = 3.2.9-NAPI
Broadcom NetXtreme II GbE Family of Adapters	Driver version (bnx2) = 2.0.23b
Broadcom NetXtreme GbE Family of Adapters	Driver version (tg3) = 3.115j
Broadcom NetXtreme II 10 GbE (57710/57711) Family of Adapters	Driver version (bnx2x) = 1.62.15
Broadcom iSCSI Offload Engine (iSOE)	Driver version (bnx2i) = 2.6.2.4c
NIC Teaming	
Native teaming driver	Driver version (bonding) = 3.4.0

Qlogic HBAs

QLE 2460, QLE 2462	Bios = 2.10; Driver version = 8.03.01.04.05.05-k
QLE 2560, QLE 2562	Bios = 2.10; Driver version = 8.03.01.04.05.05-k

Emulex HBAs

LPe1150-E, LPe11002	Bios = 2.11a0; Firmware = 2.82a4; Driver version = 8.2.0.63.3p
LPe12000-E, LPe12002-E	Bios = 2.12a6; Firmware = 2.00a4; Driver version = 8.2.0.63.3p

Dell HBAs

SAS 5/e	Firmware version = 00.10.51.00.06.12.05.00,A05 Driver version = 4.00.38.02-3, A05
Dell 6Gbps SAS HBA	Firmware version = 07.02.42.00, A04 Driver version = 07.00.01.00-1, A03

Fibre Channel SAN Switches

Cisco Fibre Channel Switches	
MDS 9124	Firmware version = 3.1.2 or higher
Brocade Fibre Channel Switches	
200E, 4100, 5000, 300, 5100, 5300	Firmware version = 6.2.0c or higher

For more information, visit Dell.com/Oracle

Oracle 11g Database Standard Edition and RAC Running on Enterprise Linux 5.5



iSCSI SAN Switches	
Dell PowerConnect 54xx GbE Ethernet Switches	Firmware = V2.0.0.46, A10 or higher
Dell PowerConnect 62xx GbE Ethernet Switches	Firmware = 3.2.1.3, A23 or higher
Dell PowerConnect 8024, 8024F 10GbE Ethernet Switches	Firmware = 3.1.4.16, A06 or higher

iSCSI Storage	
Dell EqualLogic PS4000/PS6000/PS6010/PS6510	Firmware = V5.1.0 or higher
Dell PowerVault iSCSI Storage	MD3000i Firmware = 07.35.38.60 Firmware = A11; MD1000 Firmware = A04 MD32x0i Firmware = 07.75.28.60, NVSRAM = N26X0-775890-909 Firmware = A06; MD12x0 Firmware = 1.01 A00

FC Storage	
Dell Compellent SC-30/ SC-40	SCOS = V5.4.2 or higher

SAS Storage	
Dell PowerVault	MD3000 Firmware = 07.35.38.60 Firmware = A09; MD1000 Firmware = A04 MD32x0 Firmware = 07.75.28.60, NVSRAM = N26X0-775890-009 Firmware = A06; MD12x0 Firmware = 1.01 A00
Software	
Oracle	Oracle 11g R2 11.2.0.2 Standard Edition
Operating system	Redhat Enterprise Linux 5.5 with kernel 2.6.18-194.3.1 Oracle Enterprise Linux 5.5 with kernel 2.6.18-194.32.1.0.1
Dell Systems Management Tools and Documentation DVD	DVD provided by your Dell PowerEdge Server Bundle (support.dell.com)

For more information, visit Dell.com/Oracle

Oracle 11g Database Standard Edition and RAC Running on Enterprise Linux 5.5



NOTES :

1. Dell EqualLogic PS6000E/6010E are supported only to be used for Oracle Flash Recovery Area purposes.
2. PowerEdge 1950 III, R610 and R610 II only support dual port Fibre Channel HBAs. 2 single port Fibre Channel HBAs are recommended for other servers.
3. This assumes you don't need any other ports for other functions on the switch. This assumes one NIC for the public network and two teamed NICs for the private network. The two teamed NIC ports for the private network should be on separate PCI buses: one on on-board NIC, one on add on NIC card. It is recommended that two teamed NIC s are homogenous.
4. Minimum BIOS and ESM/BMC/iDRAC versions. For latest updates please go to <http://support.dell.com>.
5. Dell Compellent Storage only supports Qlogic HBA model QLE24xx.

For more information, visit Dell.com/Oracle